



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5016A

0.8 - 2.0 GHz
25 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5016A is a 25 Watt broadband amplifier that covers the 0.8 – 2.0 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5016A comes with an extended multiyear

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	0.8 – 2.0 GHz
2	Saturated Output Power	25 Watts typical
3	Power Output @ 1dB Comp.	20 Watts min
4	Small Signal Gain	+44 dB min
5	Small Signal Gain Flatness	± 1.5 dB max
6	IP ₃	+53 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 20 Watts
9	Spurious Signals	< -60 dBc typical @ 20 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	220 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
Mechanical		
16	Dimensions	19" x 5.25" x 20"
17	Weight	38 Lbs.
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



FE Model Shown

ORDERING MODELS

- ◇ RE - Rear RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232
- ◇ FE - Front RF Connector model with Front Panel Controller Ethernet, IEEE-488 and RS232
- ◇ R - Rear RF Connector model
- ◇ F - Front RF Connector model



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5016A

0.8 - 2.0 GHz
25 WATTS
LINEAR POWER RF AMPLIFIER

FRONT PANEL CONTROLLER FEATURES (*Optional*)

- ◇ Forward Power Monitoring
- ◇ Reflected Power Monitoring
- ◇ Gain Control (20 dB dynamic range of adjustment)
- ◇ Fault Status
- ◇ Full Protection Of any VSWR Condition, Open or Short, into any Phase Angle
- ◇ Remote Control Access via the Ethernet, RS-232, or IEEE-488 Communications ports
- ◇ Integrated Automatic Leveling Control to allow end-user to maintain output even with variances in temperature, or input RF level
- ◇ Standby/Enable Control
- ◇ Front Panel Display for easy viewing of System Status Locally
- ◇ Keypad buttons for full local control

CIRCUIT CONTROL (*WITH FRONT PANEL CONTROLLER*)

- ◇ Standby (amplifier disable)
- ◇ Gain/power setting with 20dB range
- ◇ VSWR protection Reset
- ◇ ALC On/ Off

CIRCUIT INDICATIONS (*WITH FRONT PANEL CONTROLLER*)

- ◇ Forward Power
- ◇ Reflected power
- ◇ VSWR Fault
- ◇ Temp Fault
- ◇ Gain Setting (VVA) percentage

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage
- ◇ Open or Short VSWR Conditions (*With Front Panel Controller*)

RFPA SYSTEM OPTIONS

- ◇ Switched Filter Bank
- ◇ Input Power Requirements
- ◇ Ruggedized Version
- ◇ Cabinet Requirements
- ◇ Outdoor Version
- ◇ Sample Ports
- ◇ Racking Options
- ◇ Many More!
- ◇ **Consult Factory with Specific Requirements**

