



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 4010FE-015

**800 - 1000 MHz
300 WATTS
LINEAR POWER RF AMPLIFIER**

Solid State Band-specific High Power RF Amplifier

The 4010FE-015 is a 300 Watt band-specific amplifier that covers the 800 – 1000 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. The 4010FE-015 has the RF connectors located on the Front of the amplifier and communication ports on the Rear.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	800 – 1000 MHz
2	Saturated Output Power	300 Watts typical
3	Power Output @ 1dB Comp.	150 Watts min
4	Small Signal Gain	+56 dB min
5	Small Signal Gain Flatness	± 1.5 dB max
6	IP ₃	+58 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 150 Watts
9	Spurious Signals	< -60 dBc @ 150 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	1600 Watts max
12	AC Input	180 – 265 VAC, single phase
13	RF Input	0 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
16	Customized Software	Set as Master Controller
Mechanical		
17	Dimensions	19" x 8.75" x 20"
18	Weight	80 lb. max
19	Connectors	Type-N
20	Grounding	Chassis
21	Cooling	Internal Forced Air
Environmental		
22	Operating Temperature	0° C to +50° C
23	Operating Humidity	95% Non-condensing
24	Operating Altitude	Up to 10,000' Above Sea Level
25	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

CIRCUIT INDICATIONS

- ◇ Forward Power
- ◇ Reflected power
- ◇ VSWR Fault
- ◇ Temp Fault
- ◇ Gain Setting (VVA) percentage

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

COMMUNICATION

- ◇ Ethernet
- ◇ IEEE-488

AMPLIFIER OPTIONS USING 6900002 (RF RELAY)

- ◇ Can be Used as standalone amplifier
- ◇ Can be Used in Group Mode with 5163FE-015 and 5125FE-015