



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5022A-002

0.8 - 2.0 GHz
50 WATTS

Solid State Broadband High Power RF Amplifier

The 5022A-002 is a 50 Watt broadband amplifier that covers the 0.8 – 2.0 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5022A-002 comes with an extended

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	0.8 – 2.0 GHz
2	Saturated Output Power	50 Watts typical
3	Power Output @ 1dB Comp.	40 Watts min
4	Small Signal Gain	+48 dB min
5	Small Signal Gain Flatness	± 1.5 dB max
6	IP ₃	+56 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc max @ 40 Watts
9	Spurious Signals	> -60 dBc typical @ 40 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	400 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
Mechanical		
16	Dimensions	19" x 3.5" x 18"
17	Weight	30 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

CIRCUIT PROTECTIONS

- ◇ 2.5:1 Load VSWR Protection
- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage
- ◇ RF Inhibit

ORDERING MODEL

- ◇ RE - R model w/Control Option



RE Model Shown