



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)577-9887
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5063-055

1.0 - 2.0 GHz
200 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5063-055 is a 200 Watt broadband amplifier that covers the 1.0 – 2.0 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5063-055 comes with an extended multiyear warranty.

	Parameter	Specification @ 25°C
Electrical		
1	Frequency Range	1.0 – 2.0 GHz
2	Saturated Output Power	200 Watts typical
3	Power Output @ 1dB Comp.	150 Watts min
4	Small Signal Gain	+54 dB min
5	Small Signal Gain Flatness	± 2.0 dB max
6	IP ₃	+62 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 150 Watts
9	Spurious Signals	> -60 dBc
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	1500 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+10 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	A/AB
Mechanical		
16	Dimensions	19" x 8.75" x 20"
17	Weight	80 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice

-055 OPTIONS

- ◇ INPUT AND OUTPUT SAMPLE PORTS
- ◇ Input Sample -9dB +/-1.25dB
- ◇ Output Sample -44.5 +/-0.5dB

ORDERING MODELS

- ◇ R - Rear Panel Connectors
- ◇ F - Front Panel Connectors
- ◇ RE - R model w/Control Option
- ◇ FE - F model w/Control Option



FE Model Shown

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage