



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5067

20 - 1000 MHz
500 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5067 is a 500 Watt broadband amplifier that covers the 20 – 1000 MHz frequency range. This amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5067 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	20 – 1000 MHz
2	Saturated Output Power	500 Watts typical
3	Power Output @ 1dB Comp.	250 Watts min
4	Small Signal Gain	+58 dB min
5	Gain Flatness	± 2.5 dB max
6	IP ₃	+60 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-15 dBc typical @ 250 Watts
9	Spurious Signals	> -60 dBc typical @ 250 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	5000 Watts max
12	AC Input	200 – 240 VAC, single phase
13	RF Input	0 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
Mechanical		
16	Dimensions	31" x 24" x 26"
17	Weight	190 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

CIRCUIT PROTECTIONS

- ◇ Thermal Shutdown
- ◇ Built-in Current Monitoring
- ◇ Over Voltage
- ◇ Fast High Output VSWR Protection
- ◇ RF Input Overdrive Protection

ORDERING MODELS

- ◇ FE - Front panel RF connectors with controller option, and full communication ports.

