



5300 Beethoven Street, Los Angeles, CA 90066

TEL: (310)306-5556 • FAX: (310)577-9887

WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

## MODEL 5075-001

20 - 500 MHz

1000 WATTS

### Solid State Broadband High Power RF Amplifier

The 5075-001 is a 1000 Watt broadband amplifier that covers the 20 – 500 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR<sub>RF</sub> amplifiers, the 5075-001 comes with an extended

|                      | Parameter                | Specification @ 25° C         |
|----------------------|--------------------------|-------------------------------|
| <b>Electrical</b>    |                          |                               |
| 1                    | Frequency Range          | 20 – 500 MHz                  |
| 2                    | Saturated Output Power   | 1000 Watts typical            |
| 3                    | Power Output @ 1dB Comp. | 600 Watts min                 |
| 4                    | Small Signal Gain        | +61 dB min                    |
| 5                    | Gain Flatness            | ± 2.0 dB                      |
| 6                    | IP <sub>3</sub>          | +64 dBm typical               |
| 7                    | Input VSWR               | 2:1 max                       |
| 8                    | Harmonics                | -15 dBc typical @ 600 Watts   |
| 9                    | Spurious Signals         | > -60 dBc typical @ 600 Watts |
| 10                   | Input/Output Impedance   | 50 Ohms nominal               |
| 11                   | DC Input Current         | 400 Amps max                  |
| 12                   | DC Input                 | 24 VDC nominal                |
| 13                   | RF Input                 | 0 dB max                      |
| 14                   | RF Input Signal Format   | CW/AM/FM/PM/Pulse             |
| 15                   | Class of Operation       | AB                            |
| <b>Mechanical</b>    |                          |                               |
| 16                   | Dimensions               | 41" x 24" x 25" (H x W x D)   |
| 17                   | Weight                   | 550 lb. max (TBD)             |
| 18                   | RF Connectors            | Type-N                        |
| 19                   | Grounding                | Chassis                       |
| 20                   | Cooling                  | Internal Forced Air           |
| <b>Environmental</b> |                          |                               |
| 21                   | Operating Temperature    | 0° C to +50° C                |
| 22                   | Operating Humidity       | 95% Non-condensing            |
| 23                   | Operating Altitude       | Up to 10,000' Above Sea Level |
| 24                   | Shock and Vibration      | Normal Truck Transport        |

Specifications subject to change without notice.

### ORDERING MODELS

- ◇ R - Rear Panel Connectors
- ◇ F - Front Panel Connectors
- ◇ RE - R model w/Control Option
- ◇ FE - F model w/Control Option
- ◇ RT - RE model w/Ethernet Interface
- ◇ FT - FE model w/Ethernet Interface

### CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage