



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)821-7413
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5190R-900

2 - 6 GHz
9 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5190R-900 is a 9 Watt broadband amplifier that covers the 2 – 6 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability.

	Parameter	Specification @ 25° C
<u>Electrical</u>		
1	Frequency Range	2 – 6 GHz
2	Saturated Output Power	9 Watts Minimum
3	Small Signal Gain	+40 dB min
4	Power Flatness	+ 2.5 dB max
5	IP ₃	+46 dBm typical
6	Input VSWR	2:1 max
7	Harmonics	-20 dBc typical
8	Spurious Signals	< -60 dBc typical
9	Input/Output Impedance	50 Ohms nominal
10	AC Input Power	300 Watts max
11	AC Input	100 – 240 VAC, single phase
12	RF Input	+3 dBm max
13	RF Input Signal Format	CW/AM/FM/PM/Pulse
14	Class of Operation	AB
<u>Mechanical</u>		
15	Dimensions	19" x 5.25" x 20"
16	Weight	43 lb. max
17	Connectors	Type-N
18	Grounding	Chassis
19	Cooling	Internal Forced Air
<u>Environmental</u>		
20	Operating Temperature	0° C to +50° C
21	Operating Humidity	95% Non-condensing
22	Operating Altitude	Up to 10,000' Above Sea Level
23	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

FEATURES

- ◇ Customer Specific Front Panel
- ◇ Rear Panel Mounted DB9-Female for External RF Enable / Standby Control

NOTE: Pin 5 is GND, Pin 1 is the Control Line.

- IF Pin 1: OPEN - RF Standby Condition (Nominal Gain - 30dB min.)
- IF Pin 1: GND - RF Enabled (Amplifier in Normal Operation) (< 100mA to Activate)



R Model Shown