



5300 Beethoven Street, Los Angeles, CA 90066  
 TEL: (310)306-5556 • FAX: (310)821-7413  
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

**MODEL 5193-001**  
**2.5 - 6 GHz**  
**50 WATTS**  
**LINEAR POWER RF AMPLIFIER**

### Solid State Broadband High Power RF Amplifier

The 5193-001 is a 50 Watt broadband amplifier that covers the 2.5 – 6 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability.

	Parameter	Specification @ 25° C
<b>Electrical</b>		
1	Frequency Range	2.5 – 6 GHz
2	Saturated Output Power	50 Watts typical
3	Power Output @ 1dB Comp.	30 Watts min
4	Small Signal Gain	+50 dB min
5	Power Flatness	± 1 dB max
6	IP <sub>3</sub>	+54 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 30 Watts
9	Spurious Signals	> -60 dBc typical @ 30 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	800 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	0 dBm
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
<b>Mechanical</b>		
16	Dimensions	19" x 5.25" x 18"
17	Weight	48 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<b>Environmental</b>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

### CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage
- ◇ VSWR

### OTHER FEATURES

- ◇ RF output Coupling port @ 53dB below peak power

### ORDERING MODELS

- ◇ RE - Rear Panel with RS232 & IEEE
- ◇ FE - Front Panel with RS232 & IEEE
- ◇ RT - Rear Panel with Ethernet Interface
- ◇ FT - Front Panel with Ethernet Interface