



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5205-25

**0.5-2.5 GHz
100 WATTS
LINEAR POWER RF AMPLIFIER**

Solid State Broadband High Power RF Amplifier

The 5205-25 is a 100 Watt broadband amplifier that covers the 0.5-2.5 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	0.5-2.5 GHz
2	Saturated Output Power	100 Watts Typical
3	Small Signal Gain	+51 dB min
4	Power Flatness	± 2.5 dB max
5	IP ₃	+54 dBm typical
6	Input VSWR	2:1 max
7	Harmonics	-20 dBc typical
8	Spurious Signals	< -60 dBc typical
9	Input/Output Impedance	50 Ohms nominal
10	AC Input Power	2500 Watts max
11	AC Input	100 – 240 VAC, single phase
12	RF Input	10 dBm maximum 0 dBm nominal for Rated Power
13	RF Input Signal Format	CW/AM/FM/PM/Pulse
14	Class of Operation	A/AB
Mechanical		
15	Dimensions	19" x 5.25" x 20"
16	Weight	60 lb. max
17	Connectors	Type-N
18	Grounding	Chassis
19	Cooling	Internal Forced Air
Environmental		
20	Operating Temperature	0° C to +50° C
21	Operating Humidity	95% Non-condensing
22	Operating Altitude	Up to 10,000' Above Sea Level
23	Shock and Vibration	Normal Truck Transport

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

CIRCUIT CONTROL w Controller Option

- ◇ Standby (amplifier disable)
- ◇ Gain/power setting with 25dB range
- ◇ VSWR protection Reset
- ◇ ALC On/ Off

CIRCUIT INDICATIONS w controller option

- ◇ Forward Power
- ◇ Reflected power
- ◇ VSWR Fault
- ◇ Temp Fault
- ◇ Gain Setting (VVA) percentage

ORDERING MODELS

- ◇ RE - R model with Controller Ethernet, IEEE488 and RS232
- ◇ FE - F model with Controller Ethernet, IEEE488 and RS232

Specifications subject to change without notice



RE Model Shown