



5300 Beethoven Street, Los Angeles, CA 90066
 TEL: (310)306-5556 • FAX: (310)577-9887
 WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5303036A

1 - 500 MHz
3 WATTS

Solid State Broadband High Power RF Amplifier

The 5303036A is a 3 Watt broadband amplifier that covers the 1 – 500 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5303036A comes with an extended

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	1 – 500 MHz
2	Saturated Output Power	3 Watts typical
3	Power Output @ 1dB Comp.	2 Watts min
4	Small Signal Gain	+34 dB min
5	Gain Flatness	± 1.0 dB max
6	IP ₃	+39 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 2 Watts
9	Spurious Signals	> -60 dBc typical @ 2 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current @ 2W	500 mA
12	DC Input	24 – 30 VDC nominal
13	RF Input	0 dBm
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
Mechanical		
16	Dimensions	2.8" x 1.7" x 0.8"
17	Weight	0.5 lb. max
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Heatsink Required
Environmental		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.

