



5300 Beethoven Street, Los Angeles, CA 90066  
TEL: (310)306-5556 • FAX: (310)577-9887  
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

## MODEL 5303039D

**20 - 1000 MHz**  
**70 WATTS**  
**LINEAR POWER RF AMPLIFIER**

### Solid State Broadband High Power RF Amplifier

The 5303039D is a 70 Watt broadband amplifier that covers the 20 – 1000 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3<sup>rd</sup> order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR<sub>RF</sub> amplifiers, the 5303039D comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
<b><u>Electrical</u></b>		
1	Frequency Range	20 – 1000 MHz
2	Saturated Output Power	70 Watts typical
3	Power Output @ 1dB Comp.	30 Watts min
4	Small Signal Gain	+22 dB min
5	Gain Flatness	± 2.0 dB max
6	IP <sub>3</sub>	+51 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 30 Watts
9	Spurious Signals	< -60 dBc typical @ 30 Watts
10	Input/Output Impedance	50 Ohms nominal
11	DC Input Current	16 Amps max
12	DC Input	28 VDC nominal
13	RF Input	+30 dBm nominal
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
<b><u>Mechanical</u></b>		
16	Dimensions	7.2" x 7.2" x 1.1"
17	Weight	4 lb. max
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Heatsink Required
<b><u>Environmental</u></b>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

Specifications subject to change without notice.



#### Application Note:

To achieve full Rated Power for this RF Amplifier the use of a Linear + 27dBm Signal Source/ Driver is recommended, such as the Ophir RF model 5303065 RF Amplifier.

