



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5412
CH T. 0.15 - 200 MHz
CH P. 20-1000MHz
Dual Channel 25 W
LINEAR POWER RF AMPLIFIER

**Solid State
Broadband High
Power RF Amplifier**

The 5412 is a 25 Watt broadband dual band amplifier that covers the 0.15 - 200 MHz and 20 - 1000 MHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5412 comes with an extended multiyear warranty.

	Parameter	Specification @ 25° C
<u>Electrical</u>		
1	Frequency Range	Ch. T: 0.15 - 200 MHz Ch. P: 20 - 1000 MHz
2	Saturated Output Power	25 Watts typical
3	Power Output @ 1dB Comp.	Ch. T: 15 Watts min Ch. P: 10 Watts min
4	Small Signal Gain	+44 dB min
5	Small Signal Gain Flatness	+ 2.0 dB max
6	IP ₃	+48 dBm typical
7	Input VSWR	2:1 max
8	Harmonics	-20 dBc typical @ 12 Watts
9	Spurious Signals	< -60 dBc typical @ 12 Watts
10	Input/Output Impedance	50 Ohms nominal
11	AC Input Power	400 Watts max
12	AC Input	100 – 240 VAC, single phase
13	RF Input	+3 dBm max
14	RF Input Signal Format	CW/AM/FM/PM/Pulse
15	Class of Operation	AB
<u>Mechanical</u>		
16	Dimensions	15.5" x 4.75" x 10"
17	Weight	20 lb. max
18	Connectors	Type-N
19	Grounding	Chassis
20	Cooling	Internal Forced Air
<u>Environmental</u>		
21	Operating Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

CIRCUIT PROTECTIONS

- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage



Specifications subject to change without notice.