



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 5803117

2.0-6.0 GHz
5 WATTS
LINEAR POWER RF AMPLIFIER

Solid State Broadband High Power RF Amplifier

The 5803117 is a 5 Watt broadband amplifier that covers the 2.0-6.0 GHz frequency range. This small and lightweight amplifier utilizes Class A/AB linear power devices that provide an excellent 3rd order intercept point, high gain, and a wide dynamic range.

Due to robust engineering and employment of the most advanced devices and components, this amplifier achieves high efficiency operation with proven reliability. Like all OPHIR_{RF} amplifiers, the 5803117 comes with an extended multiyear warranty.

Specifications subject to change without notice

	Parameter	Specification @ 25° C
<u>Electrical</u>		
1	Frequency Range	2.0-6.0 GHz
2	Saturated Output Power	5 Watts Min
3	Power at P1dB Compression	2 Watts Min
3	Small Signal Gain	+40 dB min
4	Gain Flatness	± 3.0 dB max
5	IP ₃	+46 dBm typical
6	Input VSWR	2:1 max
7	Harmonics	-20 dBc typical @ 5 Watts
8	Spurious Signals	< -60 dBc typical @ 5 Watts
9	Input/Output Impedance	50 Ohms nominal
10	DC Input Current	8 Amps max
11	DC Input	28 VDC nominal
12	RF Input	+0 dBm max
13	RF Input Signal Format	CW/AM/FM/PM/Pulse
14	Class of Operation	A/AB
15	On/Off	On = 5V Off = 0V
<u>Mechanical</u>		
16	Dimensions (Module) (W Heatsink and Fans)	L 5.0" x W 2.0" x H 1.0" L 8.5" x W 5.2" x H 3.5"
17	Weight (W Heatsink and Fans)	4.5 Lbs.
18	Connectors	SMA female
19	Grounding	Chassis
20	Cooling	Adequate Heatsink Required
<u>Environmental</u>		
21	Baseplate Temperature	0° C to +50° C
22	Operating Humidity	95% Non-condensing
23	Operating Altitude	Up to 10,000' Above Sea Level
24	Shock and Vibration	Normal Truck Transport

FEATURES:

Heatsink and Fans Included
Enable/Disable Pin

