



5300 Beethoven Street, Los Angeles, CA 90066
TEL: (310)306-5556 • FAX: (310)821-7413
WEB: www.ophirrf.com • E-MAIL: sales@ophirrf.com

MODEL 7024

**10 - 6000 MHz
5 WATTS
BANDED POWER RF AMPLIFIER**

Solid State Broadband High Power RF Amplifier

The 7024 is a multi channel broadband system that covers the 10 - 6000 MHz frequency range with a single RF input and Single RF output port.

This integrated system provides 5W power as specified in the spec for any selected frequency range.

The system includes RF high power switches controlled by the system controller. The RS232/Ethernet and/or Front panel key-pad provides full control and reduces the power consumption to the minimum by shutting down the un-selected channel.

The System is configured in a Rear panel Connectors configuration.

	Parameter	Specification @ 25° C
Electrical		
1	Frequency Range	10 - 6000 MHz
2	Saturated Power Output	5 Watts typ. @ 10 to 1000 MHz 5 Watts typ. @ 1000 to 2000 MHz 5 Watts typ. @ 2000 to 6000 MHz
3	Nominal RF drive for rated power	0 dB typ.
4	Input VSWR	2:1 max
5	Harmonics	-15 dBc typ.
6	Spurious Signals	< -60 dBc typical
7	Temperature Protection	Baseplate above 80° C
8	AC Power Consumption (one channel transmits)	500W
9	AC Power Input	100-240VAC, 1Ø single Phase
10	Maximum RF Input	+3 dBm max
11	Antenna Switching time	100mS max
Mechanical		
12	Dimensions	19" x 26" x 5.25"
13	Weight	50 lb. max
14	Connectors	Type-N
15	Grounding	Chassis
16	Cooling	Internal Forced Air
Environmental		
17	Operating Temperature	0° C to +50° C
18	Operating Humidity	95% Non-condensing
19	Operating Altitude	Up to 10,000' Above Sea Level
20	Shock and Vibration	Normal Truck transport

Specifications subject to change without notice

CIRCUIT CONTROL

- ◇ Standby (amplifier disable)
- ◇ Gain/power setting with 25dB range
- ◇ Temp Fault
- ◇ Band Selection

CIRCUIT INDICATIONS

- ◇ Forward Power
- ◇ Reflected power
- ◇ VSWR Fault
- ◇ Temp Fault
- ◇ Gain Setting (VVA) percentage

CIRCUIT PROTECTIONS

- ◇ Infinite VSWR
- ◇ Thermal Overload
- ◇ Over Current
- ◇ Over Voltage

